!!! Use links only as references

Component	image	Num. of pieces	link
Lead Screw T8 L300		2 (for z axis)	Such as this
Linear motion rods 8x400 mm		4 (2 for y axis, 2 for z axis)	Such as this
Linear motion rods 8x350 mm		2 (for x axis)	Such as this
Brushless DC Cooling Blower Fan 5015s (50x15mm)		1 (for extruder head)	Such as this
E3D V6 All Metal Hot End (with 30x30 cooling fan, 12V heater, thermistor and PTFE (1.75mm) coupling)		1 (for extruder head)	Such as this
PTFE Teflon Tube for 1.75 Filament (2.0mm ID/4.0mm OD)		1 m (should be sufficient)	Such as this
MK8 Drive Gear (5mm bore, 40 teeth)		1 (for extruder drive)	Such as this

Nema 17 Stepper Motor (1.7A, 1.8 degree, 40mm High)		4 (1 for each axis + 1 for extruder drive)	Such as this
623ZZ (3x10x4 mm) Ball Bearing		1 (for extruder drive)	Such as this
GT2 36 Teeth 8mm Bore Timing Belt Pulley	ALLAN MARKET	2 (for z axis)	Such as this
608-2RS (8x22x7 mm) Ball Bearing	20-pack	6 (4 for z axis rods mount and 2 for spool holder)	Such as this
GT2 6mm Width 2mm Pitch Timing Belt		4 m (for z axis closed loop belt is needed ~760mm)	Such as this
GT2 Timing Belt Pulley, 20 Teeth, 5mm Bore, 6mm Belt Width		3 (for axes motors)	Such as this
GT2 Toothed Timing Belt Idler Pulley, 3mm Bore, 20 Teeth, 6mm Width Timing Belt		2 (for x and y axis)	Such as this

GT2 Toothless Timing Belt Idler Pulley, 3mm Bore, 6mm Width Timing Belt		2 (for z axis belt timing)	Such as this
Heated Bed Compression Spring 20x7.5 mm	ORIGINAL DE	5 (4 for bed leveling and 1 for extruder drive)	Such as this
LJ12A3-4-Z/BY Inductive Proximity Sensor, 4mm		1 (for z axis homing)	Such as this
MK2B PCB Heated Bed, 12V/24V, 214x214 mm (with thermistor)		1	Such as this
3D Printer Kit with RAMPS 1.4 Controller, Mega 2560 board, 4x A4988 (or DRV825) Stepper Motor Driver with Heatsink, LCD 2004 Graphic Smart Display Controller Module		1	Such as this
Mechanical Limit Switch	TA PASY AD DE	2 (for x and y homing)	Such as this
40x20x2mm Aluminum Rectangular Tube		2.4 m (4x400 mm+3x260 mm for frame assembly)	

Helios OPTO 12V 20A 250W power supplay	19-2000 HELROS OPTO LED DRIVER 12V 20A	1	
Bunch of M4 bolts and nuts and few of M3 and M5			